



LIQUID LEAK DETECTION SYSTEMS

FG-BBOX

Digital Black Box

Product Datasheet



- ▶ FG-NET Satellite Device
- ▶ Digital, Fully Addressable
- ▶ Monitoring Up to 3937 ft (1200m) Sense Cables
- ▶ Location of Faults to +/- 3 ft (1m)

Description

The FG-BBOX is a satellite device of the TTK FG-NET Digital Unit. It is monitored by FG-NET via a standard Ethernet network. It expands FG-NET to manage two additional circuits of sense cables with up to 3937 ft (1200 m) of additional Sense Cables.

The FG-BBOX can be connected with all TTK Digital Sense Cables, for water, acids and oil leak detection.

The FG-BBOX has the same advanced functionalities as FG-NET with multiple simultaneous leak location to 3 ft (1 m) accuracy. All command and control is centralised to the FG-NET, FG-BBOX is not equipped with display so it can be discretely located.

FG-BBOX connects to the FG-NET through the facilities Ethernet network, eliminating the need for additional connections.

In the event of a fault on the sense cables connected to the FG-BBOX, the relevant relay contact is activated and the LED on the relevant circuit switched to red.

On the FG-NET unit, the alarm appears on its touch screen, the responses are identical as a fault on the sense cable physically connected on the FG-NET unit.

Features & Benefits

FEATURES

- Up to 80 Digital Sense Cables can be managed independently providing a maximum protected length of 3937 ft (1200m) for the both circuits.
- No physical jumper cable or distance limit between FG-NET unit and FG-BBOX.
- Up to 25 FG-BBOX can be connected to one FG-NET unit without exceeding a total number of 500 Digital Sense Cables per FG-NET.
- TCP/IP connection via standard RJ45 socket.
- Relay type: Volt Free Contact NO/NC.
- 4 Relay contacts: 2 leak relays (1 for each circuit), 1 cable break relay and 1 power failure relay.

BENEFITS

- Multiple simultaneous leaks can be detected and located (80 cables = 80 alarms).
- Different types of sense cables can be connected on the same panel for a truly bespoke system (Water, Acids, Oils)
- Each sense cable is addressable and can be assigned a specific name.
- Cable break faults can be detected (to the nearest cable). When a cable break occurs, the system maintains its integrity by continuing to monitor all preceding cables for faults.
- Extension and upgrade of the system is easy.

Product Diagram



Technical Data

Compatibility	Digital unit: FG-NET Sense cables (digital): FG-EC, FG-AC, FG-OD range Sense cables (analogue through FG-DTCS box): FG-ECS, FG-ACS
Dimension	6.89" W x 8.66" H x 2.17" D (175 mmW x 220 mmH x 55 mmD)
Maximum Length of Sense Cable	80 lengths of sense cable (40 per circuit)
Accuracy	+/- 3 ft (1 m)
IT Security	TCP/IP connection (IPv4, IPv6) & MODBUS/JBUS Secure connection (Log-In Trap, HTTPS with TLS1.2, RFC 5280: X.509 (PKIC and CRL profile), IEEE 802.1X support, RADIUS or EAP-TLS)
System Capacity	Up to 25 FG-BBOX can be monitored by 1 FG-NET
Supply Voltage	100-240VAC 0.35A 50/60Hz
Maximum Power Consumption	15W
Working Temperature Range	5° to 131°F (-15°C to 55°C)
Working Humidity Range	5% to 80% non-condensing
Relay Types	Volt free contact (NO, NC, COM)
Relay Numbers	4
Connectivity	RJ45
Maximum Relay Switching Voltage	125 V AC and 220 V DC
Maximum Relay Switching Capacity	60 W (30V x 2A)
Ingress Protection	IP40 - indoor use only

Identification Codes

FG-BBOX (Wall mounted)	FG-NET's Satellite Device - 2 Circuits Black Box (Wall Mounted) 100-240VAC
FG-NET (Wall mounted / Rack mounted)	Digital Touchscreen Leak Detection Panel 100-240VAC
FG-EC, FG-AC, FG-OD	Digital Sense Cables in 9, 22, 49 ft (3, 7, 15m) Lengths (9, 22, 39 ft (3, 7, 12m) for FG-OD)
Accessories	
FG-DTC	Diversion Box for 'TTK Bus 8723'
FG-DTCS	Addressable Box for Water or Acids Cable, on 'TTK Bus 8723' (Sector Mode)
FG-DCTL	'Cut-To-Length' Addressable Box for Water or Acids Cable, on 'TTK Bus 8723' (Sector Mode)
FG-DOD	Bus Interface, for Integration of FG-OD Cables
FG-CLC	Leader Cable 11.48 ft (3.5 m), on 'TTK Bus 8723'
FG-TMC	Digital End Plug for Water or Acids Cables

Certificates



FG-OD sense cables which are certified by ATEX can be connected to the FG-BBOX digital black box.

All the connections in the FG-BBOX must be done with the power supply switched off. Read carefully the installation procedure for the FG-NET digital unit.

This brochure has been carefully prepared to ensure technical accuracy but is only intended for promotional use. TTK cannot guarantee that the information contained herein contains no errors or omissions, and hence does not accept responsibility related to the use of its equipment. TTK maintain its obligations set forth in the Standard Terms and Conditions of Sale and will not, under any circumstances, assume liability for any incidental damages, indirect or consequential, arising from the sale, resale, use or misuse of this product. The purchaser(s) accept their responsibility as the sole judge(s) of the adaptability of the product for the intended use.
FG-NET, FG-SYS and TOPSurveillance are trademarks of TTK S.A.S. © TTK 2025