



LIQUID LEAK DETECTION SYSTEMS

# FG-NET

## Digital Unit for Leak Detection and Location

### Product Datasheet



- ▶ Digital, Fully Addressable
- ▶ Monitoring Up to 500 Sense Cables
- ▶ Touchscreen Interface
- ▶ Instant Locating of Faults
- ▶ Integrated Monitoring Software
- ▶ TCP/IP & MODBUS/JBUS Connection

## Description

The FG-NET digital unit is designed to be used with all TTK digital sense cables, for water, bases, acids and hydrocarbon leak detection.

### In the event of a fault on the sense cables (leak or cable break):

#### Primary responses from the FG-NET:

- An audible alarm is triggered and a relay is activated.
- The touchscreen of the panel displays the location of the leak and details of the fault (the type of fault leak or cable break), including the time and date the fault is registered.
- Optional – integrated maps of the leak detection installation highlighting the location of the fault, available on the touchscreen display of FG-NET.

#### Secondary advanced responses :

- Report to the BMS via a JBUS/MODBUS protocol. The FG-NET can drive dynamic drawings on the host BMS.
- Send email alerts and SNMP traps to a LAN-connected BMS, via a standard Ethernet connection.

## Key Advantages

- Precise & Reliable Leak Detection: Instantly detects and pinpoints leaks with +/-3 ft (1 m) accuracy for water and acid leaks and to the section for oil leaks.
- Independent Cable Monitoring: The reaction time is adjustable for each cable, and each sense cable is fully addressable with a custom name for easy identification.
- Advanced Fault Management: Detects multiple simultaneous leaks (up to 120 alarms for 120 cables) and maintains system integrity by continuing to monitor all preceding cables in case of a break.
- Flexible Isolation & Configuration: Offers temporal isolation (up to 72 hours) on selected cables and provides different security levels to ensure maximum protection.
- User-Friendly & Scalable System: Features a 7" touchscreen, non-volatile memory (SD card) for storing settings and drawings, and easy expansion without additional power sources or zoning panels.
- Seamless Integration & Smart Alerts: Communicates with BMS via TCP/IP & MODBUS/JBUS, and sends real-time alerts via email and SNMP traps for proactive monitoring.

## Touchscreen Menus


### Four menus available for configuration of the FG-NET :

<b>Setup</b>	Main page for setting up the system architecture, cable isolation and reaction time rules, acknowledge mode, user access, relay status, time zone, language, sound alarm, serial links and network functionalities. An administrator level password is required to access this menu.
<b>Event log</b>	For viewing the recorded alarm history. A maximum of 5000 events can be displayed on the screen.
<b>Cables</b>	To give the user a general overview of the site installation. The interactive floor plan can be viewed under this menu as an optional feature.
<b>Help</b>	Provides troubleshooting procedures, contact details of the manufacturer and the reference number of the unit.


# Screen Shots



Simultaneous alarms displayed on one screen



Dynamic map shows leak in real time



Easy setup of relays for each cable



User-friendly interface of configuration

## Technical Data

<b>Compatibility</b>	Digital sense cables: FG-EC, FG-AC, FG-OD range of cables Analog sense cables (via diversion box): FG-ECS, FG-ACS Satellite devices: FG-BBOX, FG-RELAYS Diversion / Interface boxes: FG-DTC, FG-DTCS, FG-DCTL, FG-DOD
<b>Dimensions &amp; Weight</b>	Wall mounted: W: 8.98" W x 11.93" H x 2.64" D (228 mm W x 303 mm H x 67 mm D) Weight: 4.4 lb (2 kg) Rack mounted: 19" W x 3" H x 2.91" D (483 mm W x 177 mm H x 74 mm D) Weight: 6.61 lb (3 kg)
<b>Sensor Capacity</b>	500 sense cables (500 x 49 ft = 24 500 ft or 500 x 15 m = 7500 m) when use with FG-BBOX
<b>Location Accuracy</b>	Water & acids leak detection: +/- 3 ft (1 m); Oil leak detection: section
<b>Operating Languages</b>	English, French, German
<b>Supply Voltage</b>	100-240 VAC, 50/60 Hz
<b>Current</b>	0.3 A (120 V), 0.16 A (230 V)
<b>Power Consumption</b>	36 VA Max
<b>Operating Temperature</b>	5°F to 131°F ( -15°C to 55°C)
<b>Case Type</b>	ABS flame retardant UL94V0
<b>Screen Size</b>	7"
<b>Format</b>	Wall mounted & 19" rack mounted
<b>Ingress Protection</b>	IP40 - Indoor use only
<b>Serial Connection</b>	MODBUS/JBUS RS232 or RS422/485
<b>IT Security</b>	TCP/IP connection (IPv4, IPv6) & MODBUS/JBUS Secure connection (Log-In Trap, HTTPS with TLS1.2, RFC 5280: X.509 (PKIC and CRL profile), IEEE 802.1X support, RADIUS or EAP-TLS)
<b>Network</b>	10/100BASE-T; IPv4/IPv6
<b>Numbers of Relays</b>	9 (8 + 1 power failure relay)
<b>Relay Types</b>	Volt free dry contact (NO, NC, COM)
<b>Power Failure Relay</b>	Activated on loss of supply voltage
<b>Type of Faults Available on the Configurable Relays</b>	Leak, cable break, common fault
<b>Maximum Relay Switching Voltage</b>	125 VAC and 220 VDC
<b>Maximum Relay Switching Capacity</b>	60 W (30 V x 2A)

## Identification Codes

<b>FG-NET F</b>	Digital Touchscreen Leak Detection Panel (Wall Mounted)
<b>FG-NET E</b>	Digital Touchscreen Leak Detection Panel (Rack Mounted)

## Certifications



FG-NET F and FG-NET E comply with the requirements of the generic harmonized European standards.  
ATEX certified FG-OD range of sense cables and probes can be connected to the FG-NET digital control unit.  
All the connections in the FG-NET digital unit must be done with the power supply switched off.  
Read carefully the installation procedure for the FG-NET digital unit.

This brochure has been carefully prepared to ensure technical accuracy but is only intended for promotional use. TTK cannot guarantee that the information contained herein contains no errors or omissions, and hence does not accept responsibility related to the use of its equipment. TTK maintain its obligations set forth in the Standard Terms and Conditions of Sale and will not, under any circumstances, assume liability for any incidental damages, indirect or consequential, arising from the sale, resale, use or misuse of this product. The purchaser(s) accept their responsibility as the sole judge(s) of the adaptability of the product for the intended use.  
FG-NET, FG-SYS and TOPSurveillance are trademarks of TTK S.A.S. © TTK 2025

- **TTK USA Inc.** / 100 S. Broad Street, Suite 730 Philadelphia, PA 19110 / Tel. +1 610 304 2270 / [www.ttkusa.com](http://www.ttkusa.com) / [sales@ttkusa.com](mailto:sales@ttkusa.com)
- **TTK Headquarters** / 19, rue du Général Foy / 75008 Paris / France / T : +33.1.56.76.90.10 / F : +33.1.55.90.62.15 / [www.ttk.fr](http://www.ttk.fr) / [ventes@ttk.fr](mailto:ventes@ttk.fr)